

Last information update: October 2024

**Product configuration: QB14+QA86.01**

QB14: Down LO plate - DALI - General Light - LED Neutral - L 1196

QA86.01: Initial module - Frame Down - General Light - L 2397 - White

**Product code**

QB14: Down LO plate - DALI - General Light - LED Neutral - L 1196

**Technical description**

LED module set up for housing in initial or intermediate system profiles. Down emission - Low Output version for General Light profiles (with opal diffuser screen). DALI dimmable control gear integrated in the luminaire. Extruded aluminium heat sink; high emission yield flux enhancer. Neutral 4000K LED

**Installation**

Module insertion on profiles facilitated by a quick coupling system.

**Colour**

Indeterminate (00)

**Weight (Kg)**

1.28

**Wiring**

Quick coupling terminal block connection to simplify connections between the subsequent modules. Complete with integrated dimmable digital DALI control gear.

Complies with EN60598-1 and pertinent regulations

**Product code**

QA86.01: Initial module - Frame Down - General Light - L 2397 - White

**Technical description**

Initial profile in extruded aluminium - Frame version with contact frame; methacrylate opal screen for diffused general light; screen set up for connecting several lengths by overlapping.

**Installation**

Recessed using the brackets on the profile. The initial modules can be used individually (stand-alone), if completed with accessory caps and the required LED module.

**Colour**

White (01)

**Weight (Kg)**

5

**Mounting**

ceiling recessed|ceiling pendant


**Wiring**

Set up to house the LED modules required by the system.

**Notes**

Take care with the system configuration. To make continuous lines of lighting, use the intermediate modules. To complete a continuous line correctly there must always be an initial module at the start or end of the composition.

Complies with EN60598-1 and pertinent regulations

**Technical data**

Im system:	4104	Lamp code:	LED
W system:	30	Number of lamps for optical assembly:	1
Im source:	5400	ZVEI Code:	LED
W source:	30	Number of optical assemblies:	1
Luminous efficiency (Im/W, real value):	136.8	Power factor:	See installation instructions
Im in emergency mode:	-	Inrush current:	18 A / 250 µs
Total light flux at or above an angle of 90° [Lm]:	0	Maximum number of luminaires of this type per miniature circuit breaker:	B10A: 21 luminaires B16A: 34 luminaires C10A: 35 luminaires C16A: 57 luminaires
Light Output Ratio (L.O.R.) [%]:	76	Minimum dimming %:	1
CRI (minimum):	80	Overvoltage protection:	2kV Common mode & 1kV Differential mode
Colour temperature [K]:	4000	Control:	DALI-2
MacAdam Step:	3		

Polar

