iGuzzini

Last information update: June 2025

#### Product configuration: 365A.01

365A.01: SIPARIO Ø86 spotlight - CASAMBI - WideFlood - OBLens - - 18.1W 1603.7Im - 3500K - CRI 90 - White

### Product code

365A.01: SIPARIO Ø86 spotlight - CASAMBI - WideFlood - OBLens - - 18.1W 1603.7lm - 3500K - CRI 90 - White

### Technical description

Ø86 adjustable spotlight with adapter for installation on a base or electrified track. LED lamp with C.O.B. (Chip on board) technology, -CRI90- high colour rendering and 3500K tone.


Die-cast aluminium body with thermoplastic rear cap and front ring (Mass-Balance). The product can be rotated by 360° around the vertical axis with a mechanical lock and tilted by 90° relative to the horizontal plane. Passive heat dissipation. OptiBeam Lens optical system with WideFlood optic.

Body complete with dimmable power supply unit and Casambi protocol positioned inside the product track adapter. The components used allow the products to be controlled with the Casambi system app and components, enabling on-off, dimming and scene recall functions and allowing multiple luminaires to operate in a Casambi mesh network. 2.4 GHz bluetooth frequency. The app is available on the Apple Store and Google Play Store. Integrated Beacon that can be activated via an app (iBeacon) that enables smart functions for third party applications and the Jiminy Push Notification app.

Spotlight with Push&Go system designed to facilitate and safely accelerate the connection between product and optic accessory. Mechanically disconnecting the accessory allows it to be disengaged but not dropped. Three internal accessories and one external one can be used simultaneously. All internal accessories rotate 360° about the spotlight longitudinal axis.

Colour White (01)			Weight (Kg) 0.87	
Mounting three circuit track				
<b>Notes</b> Max distance between prod The maximum distance is a			lls, metal panels and the layo	ut of the system.
			Complies	with EN60598-1 and pertinent regulation
() IP20 C	€ ĽÅ	E S	CCLET	
Technical data	1001			
Im system:	1604		Life Time LED 1:	> 50,000h - L90 - B10 (Ta 25°C)
Im system: W system:	18.1		Lamp code:	LED
Im system: W system: Im source:	18.1 2030		Lamp code: Number of lamps for optical	LED
Im system: W system: Im source: W source:	18.1 2030 16		Lamp code: Number of lamps for optical assembly:	LED 1
Im system: W system: Im source: W source: Luminous efficiency (Im/W,	18.1 2030 16		Lamp code: Number of lamps for optical assembly: ZVEI Code:	LED 1 LED
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value):	18.1 2030 16 88.6		Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical	LED 1
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value): Im in emergency mode:	18.1 2030 16 88.6		Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies:	LED 1 LED 1
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above	18.1 2030 16 88.6		Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor:	LED 1 LED 1 See installation instructions
Im system: W system: Im source: Uuminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.)	18.1 2030 16 88.6 - 0		Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies:	LED 1 LED 1
Im system: W system: Im source: Uuminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) [%]:	18.1 2030 16 88.6 - 0		Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor: Inrush current: Maximum number of	LED 1 LED 1 See installation instructions 20 A / - μs
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) [%]: Beam angle [°]:	18.1 2030 16 88.6 - 0 79		Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor: Inrush current: Maximum number of luminaires of this type per	LED 1 LED 1 See installation instructions 20 A / - µs B10A: 50 luminaires B16A: 80 luminaires C10A: 83 luminaires
Im system: W system: Im source: Uuminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.)	18.1 2030 16 88.6 - 0 79 47°		Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor: Inrush current: Maximum number of luminaires of this type per miniature circuit breaker:	LED 1 LED 1 See installation instructions 20 A / - µs B10A: 50 luminaires B16A: 80 luminaires C10A: 83 luminaires C16A: 136 luminaires
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value): In in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) [%]: Beam angle [°]: CRI (minimum): Colour temperature [K]:	18.1 2030 16 88.6 - 0 79 47° 90		Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor: Inrush current: Maximum number of luminaires of this type per miniature circuit breaker: Minimum dimming %:	LED 1 LED 1 See installation instructions 20 A / - µs B10A: 50 luminaires B16A: 80 luminaires C10A: 83 luminaires C16A: 136 luminaires 1
Im system: W system: Im source: W source: Luminous efficiency (Im/W, real value): Im in emergency mode: Total light flux at or above an angle of 90° [Lm]: Light Output Ratio (L.O.R.) [%]: Beam angle [°]: CRI (minimum):	18.1 2030 16 88.6 - 0 79 47° 90 3500		Lamp code: Number of lamps for optical assembly: ZVEI Code: Number of optical assemblies: Power factor: Inrush current: Maximum number of luminaires of this type per miniature circuit breaker:	LED 1 LED 1 See installation instructions 20 A / - µs B10A: 50 luminaires B16A: 80 luminaires C10A: 83 luminaires C16A: 136 luminaires

Polar Imax=2427 cd	CIE	Lux			
90° 180° 90	nL 0.79 94-100-100-100-79 TUGR 18.7-18.7	h	d	Em	Emax
	DIN A.61	2	1.7	470	607
2500	UTE 0.79A+0.00T F"1=940	4	3.5	117	152
2500	F"1+F"2=996 F"1+F"2+F"3=1000 CIBSE	6	5.2	52	67
α=47°	LG3 L<3000 cd/m <sup>2</sup> at 65° UGR<19   L<3000 cd/mq (	a <sub>65°</sub> 8	7	29	38





Utilisation factors

R	77	75	73	71	55	53	33	00	DRR
K0.8	69	65	62	60	64	62	61	58	74
1.0	73	69	66	64	68	66	65	63	79
1.5	77	74	72	70	73	71	71	68	86
2.0	80	78	76	74	76	75	74	72	91
2.5	81	80	78	77	79	77	76	74	94
3.0	82	81	80	79	80	79	78	76	96
4.0	83	82	82	81	81	81	79	77	98
5.0	84	83	83	82	82	81	80	78	99

# Luminance curve limit

QC	Α	G	1.15	20	00		1(	000		500				<-3	00				
	в		1.50				20	000		1000	7	50		50	0		<=300	(	
	С		1.85							2000				100	00		500	<	-300
85°					T			-			$\overline{n}$	, T			-	-	T		3 8
75°		۰.			+-						μ	+	-	μ	-				- 6
65°				-	-					1	~		X	-	+		$\overline{}$		2
55°				+	+							$\rightarrow$	$\langle \rangle$				-		a h
45° .	10 <sup>2</sup>		2	3	4	5	6	8	10 <sup>3</sup>		2	3	4	5	6	8	104	cd/	 m <sup>2</sup>
	C0-18	0 -					-				C90-2	270							

# UGR diagram

Rifle	et :										
ceil/cav		0.70	0.70	0.50	0.50	0.30	0.70	0.70	0.50	0.50	0.30
walls	3	0.50	0.30	0.50	0.30	0.30	0.50	0.30	0.50	0.30	0.30
work	pl.	0.20	0.20	0.20	0.20	0.20	0.20	0.20	0.20	0.20	0.20
Roor	n dim	2251200		viewed		10.3304.033		viewed			
x	У		C	rosswis	e			endwise			
2H	2H	19.2	19.8	19.5	20.1	20.3	19.2	19.8	19.5	20.1	20.3
	ЗH	19.1	19.7	19.4	19.9	20.2	19.1	19.7	19.4	19.9	20.2
	4H	19.0	19.5	19.4	19.8	20.1	19.0	19.6	19.4	19.8	20.
	6H	18.9	19.4	19.3	19.7	20.1	19.0	19.4	19.3	19.8	20.
	BH	18.9	19.4	19.3	19.7	20.0	18.9	19.4	19.3	19.7	20.0
	12H	18.9	19.3	19.2	19.6	20.0	18.9	19.3	19.3	19.7	20.0
4H	2H	19.0	19.6	19.4	19.8	20.1	19.0	19.5	19.4	19.8	20.
	ЗH	18.9	19.3	19.3	19.7	20.0	18.9	19.3	19.3	19.7	20.0
	4H	18.8	19.2	19.2	19.6	20.0	18.8	19.2	19.2	19.6	20.
	6H	18.7	19.1	19.1	19.5	19.9	18.7	19.1	19.1	19.5	19.
	BH	18.7	19.0	19.1	19.4	19.8	18.7	19.0	19.1	19.4	19.8
	12H	18.6	18.9	19.1	19.3	19.8	18.6	18.9	19.1	19.3	19.
вн	4H	18.7	19.0	19.1	19.4	19.8	18.7	1 <u>9.0</u>	19.1	19.4	19.
	6H	18.6	18.8	19.1	19.3	19.8	18.6	18.8	19.1	19.3	19.
	BH	18.5	18.8	19.0	19.2	19.7	18.5	18.8	19.0	19.2	19.1
	12H	18.5	18.7	19.0	19.2	19.7	18.5	18.7	19.0	19.2	19.1
12H	4H	18.6	18.9	19.1	19.3	19.8	18.6	18.9	19.1	19.3	19.8
	бH	18.5	18.8	19.0	19.2	19.7	18.5	18.8	19.0	19.2	19.7
	H8	18.5	18.7	19.0	19.2	19.7	18.5	18.7	19.0	19.2	19.1
Varia	tions wi	th the ot	oserver p	osition	at spacin	g:					
S =	1.0H		4	.8- / 0.	3	4.0 / -8.3					
	1.5H		6.	7 / -12	.5	6.7 / -12.5					