Libera Stand-alone

Design Artec iGuzzini Studio

Last information update: May 2025

Product configuration: SJ87(BR)

SJ87: Linear pendant DownLight luminaire for Filorail track L=1828 - Space Frame optic - UGR<19 -



Product code

SJ87: Linear pendant DownLight luminaire for Filorail track L=1828 - Space Frame optic - UGR<19 -

Technical description

Direct emission luminaire with CRI90 monochrome LED lamps. Opti-Diamond Space optic with UGR<19 (in compliance with the standard for use in environments with video monitors) available in a White Cover (Transparent White) or Black Cover (Transparent Black) version. Frame version extruded aluminium profile with die-cast zamak end caps. Complete with power and pendant cable L=3000 that can be adjusted as required. Steel pendant mount cable with millimetric adjustment system and brass component. Complete with 48Vdc Mid-Power Led circuit and DALI dimming system. "Powerline" technology allows each product connected to the system to be adjusted separately.

Weight (Kg)

Installation

A tool-free system for connecting the product electrically and mechanically to the 48V Filorail low voltage track.



Colour

White/White Transparent (G0) | Black/Black Transparent (G1) | Black/White Transparent (G2) | White/Black Transparent (M6) | Titanium/White Transparent (P9) | Titanium/Black Transparent (Q0) | Sapphire blue/White Transparent (Q1) | Sapphire blue/Black Transparent (Q2)

Mounting

ceiling pendant

Wiring

Power supply unit (48V) to be ordered separately as specified in the instruction sheet.

Complies with EN60598-1 and pertinent regulations









Technical data			
Im system:	1583.6	MacAdam Step:	3
W system:	12.4	Life Time LED 1:	> 50,000h - L90 - B10 (Ta 25C)
Im source:	2140	Voltage [Vin]:	48
W source:	11	Lamp code:	LED
Luminous efficiency (lm/W, real value):	127.71	Number of lamps for optical assembly:	1
Im in emergency mode:	-	ZVEI Code:	LED
Total light flux at or above an angle of 90° [Lm]:	32.62	Number of optical assemblies:	1
Light Output Ratio (L.O.R.)	74	Power factor:	See installation instructions
[%]:		Overvoltage protection:	0kV Common mode & 0kV
Beam angle [°]:	62°		Differential mode
CRI:	90	Control:	DALI
Colour temperature [K]:	4000		