

## Palco Low Voltage


Design Artec  
Studio

iGuzzini

Last information update: March 2025

### Product configuration: 028B.01

028B.01: Palco LV spotlight Ø 51 - Wall Washer - BLE Casambi - 16.2W 266.1lm - 2700K - CRI 90 - White



### Product code

028B.01: Palco LV spotlight Ø 51 - Wall Washer - BLE Casambi - 16.2W 266.1lm - 2700K - CRI 90 - White

### Technical description

Miniaturised adjustable spotlight with adapter for installation on 48V low voltage track. Made of die-cast aluminium with a passive dissipation system. The adapter made of a thermoplastic material includes the DC/DC driver circuit and Bluetooth protocol. Integrated «Bluetooth Casambi» technology allows each light module on the track to be adjusted separately. The swivel joints allow the spotlight to be rotated by 360° and tilted by 90°. Thermoplastic high definition lens with extra filter for variable optic. Asymmetric screen designed to create a homogeneous effect on walls from top to bottom and avoid shadow zones near the ceiling. A rapid tool-free system for connecting the adapter electrically and mechanically to the track. Luminaire with Bluetooth Low Energy technology (Casambi). Frequency 2.4 GHz BLE. The luminaire can be controlled with the Casambi App that enables on-off, dimming and scene recall functions. The app is available on the Apple Store and Google Play Store. It can be integrated in the system's "Mesh" network that allows multiple luminaires to be controlled. OTA (over the air) update via app. Integrated Beacon that can be activated via Smart Light Control (iBeacon) that enables functions including push notification and indoor navigation-wayfinding.

### Installation

An adapter is used to fix the device mechanically and tool-free to the 48V track. Max luminaire-luminaire distance (\*): 8 m; max smartphone-luminaire distance (\*): 20 m.

### Colour

White (01)

### Weight (Kg)

0.29

### Mounting

Low voltage track

### Wiring

Direct connection on 48V track. Track power supply unit to be ordered separately. Luminaire can be controlled with Bluetooth technology (Casambi)

### Notes

To optimize vertical illumination consult the installation distance recommendations in the instructions sheet. (\*) The maximum distance for Bluetooth installations is affected by physical obstacles, like walls, metal panels and the layout of the system. We suggest that a test is conducted at the installation site.

Complies with EN60598-1 and pertinent regulations



IP20



### Technical data

lm system:	266	Life Time LED 1:	> 50,000h - L90 - B10 (Ta 25°C)
W system:	16.2	Voltage [Vin]:	48
lm source:	1400	Lamp code:	LED
W source:	15	Number of lamps for optical assembly:	1
Luminous efficiency (lm/W, real value):	16.4	ZVEI Code:	LED
lm in emergency mode:	-	Number of optical assemblies:	1
Total light flux at or above an angle of 90° [Lm]:	0	LED current [mA]:	400
Light Output Ratio (L.O.R.) [%]:	19	Power factor:	See installation instructions
CRI (minimum):	90	Minimum dimming %:	1
Colour temperature [K]:	2700	Control:	Casambi
MacAdam Step:	2		

### Polar

Imax=592 cd		C0-180		Lux	
h	d1	d2	Em	Emax	
2	1.3	1.3	110	146	
4	2.5	2.6	28	36	
6	3.8	3.9	12	16	
8	5	5.2	7	9	

α = 35° / 36°

**Isolux**

